



## Instructions For Use

### LV Rescue Kits



- ***This product is to be used by authorised industry trained personnel only.***
- ***The use of this product must adhere to appropriate work practises and or industry standards ensuring compliance to all Workplace Health and Safety Regulations.***
- ***This product may only be installed onto an asset when the asset owner has approved of such installation.***
- ***Failure to follow appropriate work practices and operational instructions or modifications to this equipment can result in product damage and or serious injury.***
- ***These instructions are to be read in conjunction with the Balmoral Engineering terms and conditions published on our website.***

It is recommended that **BALMORAL™** LV Rescue Kts should be cared for in the following manner:

#### Storage:

- To prevent premature wear of the rescue kit during work keep out of direct sunlight for long periods of time away from debris and objects that can slice or cut the Rescue kit.

Note: other storage methods may be suitable, however, if these methods have not been approved by Balmoral, then the customer takes full responsibility for their suitability.

- We recommend that Rescue kits be stored in a clean, temperature - stable environment away from sharp objects, sunlight, ozone and steam.
- Kept clear of all oil based products and hydrocarbon derivatives.

#### Use:

- Prior to commencement of work, Rescue kits should be visually inspected for any defects. Please refer to the section “Periodic Visual Inspection and Care”.
- Should any item be found to have a defect, the rescue kit should be removed from service.
- Any component that becomes soiled or dirty should be cleaned.
- See below “Periodic Visual Inspection and Care” instructions for further directions on how to clean and inspect rescue kits.

#### Periodic Visual Inspection and Care:

- It is recommended that where it is possible or practical to do so, all rescue kits be periodically inspected, cleaned and then re-inspected. This periodic inspection is recommended to take place every 6 months and should be an adjunct not a replacement for the routine (prior to use) inspection.

To aid visual inspection, materials should be:

- Cleaned to remove grime and dirt which may otherwise hide potential defects.
- Components removed from carry bag and placed on a table/workbench.
- We recommend cleaning with either a mild detergent or Polywater® Rubber Goods Cleaner for the external bag (see the “In Service Care Of Tools & Equipment” document for further details).
- If any component is found to be defective, the rescue kit should be removed from service.



- Each component of the rescue kit should be inspected for defects and relevant expiry dates.
- Defects may take the form of embedded foreign objects, cuts, abrasions, tears, cracking, rust, fraying, battery leakage, loose threads, sharpness of cutting tools and peeling.
- It is essential that components that expire are inspected and removed after the expiry date.

**Zippers:**

- It is especially important that zippers are cleaned regularly to ensure they remain free from debris and/or rust.
- While the zipper teeth are made from non-conductive materials, this should not be relied upon. Caution that the zipper slider is conductive.

**Kit Components:**

Item No	Kit Components Description	Kit Item Numbers			
		11002	11004	11022	Image*
26008	Rescue Kit Bags & Storage, 455mm (L) x 290mm (H) x 138mm (W), PVC, Orange, Velcro, Switchboard	1 EA	1 EA	1 EA	
/	Cardiopulmonary Resuscitation Card, 90mm x 220mm, Folds down to 90mm x 55mm	1 EA	1 EA	1 EA	
LV Crook	Orange LV Rescue Crook CW Black Heat Shrink Handle	1 EA	1 EA	1 EA	
CAT6L2D	LED Torch-195x55-2x D Batt/Non Conductive - Red	1 EA	1 EA	1 EA	
BAR-ISO	Rescue Kit Accessories, "Isolate Here" Sign, 260mm (W) x 180mm (H), c/w Rope, Polypropylene, White with Red Text	1 EA	1 EA	1 EA	
WFB1812	Rescue Kit Accesories, Fire Blanket, 1.8m (L) x 1.2m (W), AS3504	1 EA	1 EA	1 EA	
TYC-MTD	Rescue Kit Accessories, Trauma Dressing, 30" (L) x 10" (W), White	1 EA	1 EA		
RIG014YS11	LV Rubber insulating Rescue Gloves, Size 11, EN / IEC 60903	1 PR		1 PR	
OUTLVGS11	LV Leather Goatskin Outer Protector Gloves, Size 11 c/w Velcro tab / strap – Kevlar thread			1 EA	
26023	LV Glove Bag-400x220x75-1Poc-Canvas-Natural-Velcro			1 EA	

\* Product images displayed are representative only

**For further product information - Visit our website:**

[www.balmoralengineering.com](http://www.balmoralengineering.com)