



Compiled/Updated	Approved	Issued Date	Revision
ZB	CD	19/09/2025	1



## Fence Cover Kit Instructions For Use

- ***This product is to be used by authorised industry trained personnel only.***
- ***The use of this product must adhere to appropriate work practises and or industry standards ensuring compliance to all Workplace Health and Safety Regulations.***
- ***This product may only be installed onto an asset when the asset owner has approved of such installation.***
- ***Failure to follow appropriate work practices and operational instructions or modifications to this equipment can result in product damage and or serious injury.***
- ***These instructions are to be read in conjunction with the Balmoral Engineering terms and conditions published on our website.***

The Balmoral™ Fence Cover Kit is designed to assist in the protection of personnel from the risks of contact with electric fences commonly used in rural areas.

### 1: In-Use Instructions

1. Prior to commencement of work inspect the red PVC of the Fence cover for punctures or cuts in the material. If there are any punctures or cuts the item should be removed from service. If the fence cover is dirty or soiled, it should be cleaned. For further information refer to section “Periodic Visual inspection and care”.
2. Unfurl the Fence Cover and lay over the strongest and highest support possible. Ensure that the fence cover drapes over both sides and with the black HDPE U guard opening facing downward.
3. Once the risk of contact with an electric fence has passed, remove the Fence cover and roll the red PVC around the HDPE guard and place back into protective bag

### Warning:

This product has been tested on systems akin to commercially available electric fences operating to AS60335.2.76.

**BALMORAL™** cannot confirm proper functionality on electric fences:

- That do not comply with AS60335.2.76.
- Designed to Stun and/or Kill.
- Erected outside of Australia.
- Incorporating barbed wire or another cutting element.

Compiled/Updated	Approved	Issued Date	Revision
ZB	CD	19/09/2025	1

## 2: In Service Care

### Storage:

It is recommended that **BALMORAL™** Fence cover kits should be cared for in the following manner:

- Stored in a clean and room temperature environment away from sharp objects, sunlight, ozone and steam.
- Kept clear of oil based products and hydrocarbon derivatives.
- Transported in the supplied carry bag or a suitable storage device capable of ensuring the above conditions during work

Note: Other storage methods may be suitable, however, if these methods have not been approved by Balmoral, then the customer takes full responsibility for their suitability.

### Periodic Visual Inspection and Care:

Before and after each and every use, the fence cover should be inspected for failing connections, punctures along the red PVC or cracks along the HDPE U guard. If any failures including and beyond those stated above, the product should be removed from service

- It is recommended that where it is possible or practical to do so, that all Fence cover kits be periodically inspected, cleaned and then re-inspected. This periodic inspection is recommended to take place every 6 months and should be an adjunct, not a replacement for the routine (prior to use) inspection.

To aid visual inspection, products should be:

- Cleaned to remove grime and dirt which may otherwise hide potential defects. We recommend cleaning with a dedicated rubber goods cleaner or warm soapy water.
- Any item found to be defective, should be removed from service.
- Defects in the red PVC may take form in cuts, embedded objects, punctures.
- Defects in the HDPE U guard may take form in cracks, bending or warping

### Marking information:



Date of manufacture	Internal BE lot number	Internal BE Item code
---------------------	------------------------	-----------------------

**For more product information please visit our website:**

[www.balmoralengineering.com](http://www.balmoralengineering.com)